


Series of practical exercises 6

Exercise 1:

1. Include the provided jQuery library in your page,
2. Make two images using **Paint** containing a light bulb each, one in ON state, the other in OFF state like the follows:



3. Include one image in your page using **img** tag
4. Make two buttons **On** and **Off** to change the property **src** using jQuery method **attr(attributeName, value)**

Exercise 2:

Continue with the previous exercise

1. Make a table then use the selector **:odd** to color the lines alternatively like the figure below,

Student	Mark
Mohamed	15.00
Ali	12.00
Moussa	19.00
Aissa	14.00

2. Use the following selectors on the the table above: **:first**, **:last**

Exercise 3:

1. Include the provided jQuery library in your page,
2. Create a form with two fields **a** and **b**
3. Create a PHP script (add.php) that adds two parameters **a**, **b** and prints back the result
4. Make the required script that gets the sum of fields from PHP script using jQuery **ajax()** function:

```
1 $.ajax(  
2   {  
3     type: "POST",  
4     url: "add.php",  
5     data: $("#myform").serialize(),  
6     success: function(result){  
7       $("#result").html(result);  
8     }  
9   }  
10 )
```
